

MS8340B Mastech

kategoria: Kategorie > Mierniki - Multimeter



Kod QR:



Display: 22000 counts

Auto Ranging

Auto Power Off

Relative Measurement

Peak Measurement

Diode: 2.8V

Continuity Buzzer: <30Ω

MAX/MIN

Data hold

True RMS

Display Backlight

Low Battery Display

USB Interface: Windows OS

<i>DC Voltage</i>	220mV		+-(0.05%+3)
	2.2V/22V/220V/1000V		
<i>AC Voltage</i>	2.2V/22V/220V/700V(40~400Hz)		+-(0.8%+4)
<i>DC mV</i>	220mV(40~400Hz)		+-(0.05%+3)
<i>AC mV</i>	220mV(40~400Hz)		+-(0.8%+4)
<i>DC Current</i>	220μA/2200μA/22mA/220mA/10A		+-(0.8%+4)
<i>AC Current</i>	220μA/2200μA/22mA/220mA		+-(1.0%+3)
	10A		+-(1.5%+3)
<i>Resistance</i>	220Ω/2.2KΩ/22KΩ/220KΩ		+-(0.8%+2)
	2.2MΩ/22MΩ/220MΩ		+-(0.8%+2)
<i>Capacitance</i>	22nF/220nF/2.2μF/22μF/220μF/2.2mF/		+-(2.5%+3)
	220mF		
<i>Frequency</i>	22Hz/220Hz/2.2kHz/22kHz/220kHz		+-(0.2%+3)
<i>Duty Cycle</i>	1%~99%		-0,01