



Measuring meter Miernik MS8340A Mastech

kategoria: Kategorie > Mierniki - Multimeter



Kod QR:



- LCD Display: 6000 counts
- Auto Ranging
- Auto Power Off
- Relative Measurement
- LPF: 1KHz Low Pass Filter
- Diode: 2.8V
- Continuity Buzzer: <math><30\Omega</math>
- MAX/MIN
- Data Hold
- Display Backlight
- Low Battery Display
- DC Voltage

	600mV/6V	+-(0.5%)
	60V/600V/1000V	+-(0.8%+3)
AC Voltage	6V/60V/750V(50Hz)	+-(1.0%+4)
	6V/60V/750V(2kHz)	+-(2.0%+3)
DC Current	600μA/6mA/60mA/600mA/10A	+-(1.2%+4)
AC Current	600μA/6mA/60mA/600mA	+-(1.5%+3)
	10A	+-(2.0%+3)
Resistance	600Ω/6KΩ/60KΩ/600KΩ/6MΩ/60MΩ	-2,01
Capacitance	40nF/400nF	+-(3.0%+2)
	40n4uF/40uF/400uF	+-(3.5%+2)
Frequency	1Hz~10MHz	+-(0.2%+3)
Duty Cycle	1%~99%	-0,01
Temperature	-10°C~700°C	-2,02
	14°F~1292°F	-4,02